

Changing Registry Permissions in Windows® 2000 and XP Operating Systems



Applies to: SMART Board™ software 7, 8 and 9, and all SMART Board and Sympodium™ products on Windows® 2000 and XP operating systems

Overview

To change some settings on your SMART product, you may need to change the registry permissions in the SMART Technologies folder.

Details

To edit the registry permissions in the Windows XP operating system

1. Press **Start > Run**, and then type **regedt32**.
2. Go to **HKEY_LOCAL_MACHINE\Software**, and then select the **SMART Technologies** folder.
3. From the **Edit** menu, select **Permissions**. Check to see if **Everyone** appears in the list. If Everyone is listed, complete procedure A. Otherwise, complete procedure B.

A. If Everyone appears in the list:

- a. Select Everyone, and then select the Full Control and Read checkboxes in the Allow column.
- b. Click **Apply** and **OK**, and then exit the registry editor and restart your computer.

B. If Everyone doesn't appear in the list:

- a. Click the **Add** button.
- b. Type **Everyone** in the **Enter the object names** box.
- c. Click the **Check Names** button, and wait until Everyone is underlined.
- d. Click **OK**.
- e. Select **Everyone**, and then select the **Full Control** and **Read** check boxes in the Allow column. Click **Apply** and **OK**, and then exit the registry editor and restart your computer.

To edit the registry permissions in the Windows 2000 operating system

1. Select **Start > Run**, and type **regedt32**.
2. Go to **HKEY_LOCAL_MACHINE\Software**, and then select the **SMART Technologies** folder.
3. From the **Security** menu, select **Permissions**. Check to see if **Everyone** appears in the list. If Everyone is listed, complete procedure A. Otherwise, complete procedure B.

A. If Everyone appears in the list:

- a. Select **Everyone**, and then select the **Full Control** and **Read** checkboxes in the Allow column.
- b. Click **Apply** and **OK**, and then exit the registry editor and restart your computer.

B. If Everyone doesn't appear in the list:

- a. Click the **Add** button.
- b. Select the local network in the **Look** in box.
- c. Select **Everyone** and click the **Add** button, and then click **OK**.
- d. Select **Everyone**, and then select the **Full Control** and **Read** check boxes in the Allow column.
- e. Click **Apply** and **OK**, and then exit the registry editor and restart your computer.

First Published: May 31, 2005

Last Updated: November 23, 2007

SMART Technologies
1207 – 11 Avenue SW, Suite 300
Calgary, AB T3C 0M5
CANADA



www.smarttech.com/support www.smarttech.com/contactsupport
Support +1.403.228.5940 or Toll Free 1.866.518.6791 (Canada/U.S.)

© 2005–2007 SMART Technologies ULC. All rights reserved. SMART Board, Symposium, smarttech and the SMART logo are trademarks or registered trademarks of SMART Technologies ULC in the U.S. and/or other countries. Windows is either a registered trademark or a trademark of Microsoft Corporation in the U.S. and/or other countries. All other third-party product and company names may be trademarks of their respective owners. Patent No. US5448263; US6141000; US6326954; US6337681; US6741267; US6747636; US6803906; US6919880; US6947032; US6954197; US6972401; US7151533; US7184030; US7236162; CA2058219; EP1297488; ES2279823; CN1310126; and DE60124549. Other patents pending. Contents are subject to change without notice. 11/2007.