

# Customizing SMART Board™ Software for a USB Storage Device



**Applies to:** SMART Board™ software 9.1 for USB storage devices

## Overview

How to customize SMART Board software for your USB storage device.

## Details

Remove languages you don't need, and select the startup language or add a desktop shortcut.

### To remove languages you don't use from the SMART Board software folder

1. On your USB storage device, go to **SMART Board Software > Languages**.
2. Select the language folders you don't need and delete them. This table lists the languages and the folders that contain them.

040c	French (Standard)	0414	Norwegian (Bokmål)
0407	German (Standard)	0452	Welsh
0c0a	Spanish (Spain, International Sort)	0413	Dutch (The Netherlands)
0411	Japanese	041d	Swedish
0804	Chinese (PRC) (Simplified)	0401	Arabic (Saudi Arabia)
0404	Chinese (Taiwan) (Traditional)	0419	Russian
0412	Korean	040b	Finnish
0410	Italian (Standard)	0406	Danish
0816	Portuguese (Portugal)	0405	Czech
0416	Portuguese (Brazil)	041F	Turkish

By default, SMART Board software automatically starts in the language of your operating system.

If you want to be able to select which language SMART Board software starts in, and/or to choose to add a desktop shortcut to SMART Board software, create a new SBLConfig.ini file in the SMART Board software folder.

### To create the SBLConfig.ini file

1. On your USB storage device, open the **SMART Board Software** folder, and then open the Languages folder.
2. Go to the **File** menu and select **New > Text File**.

A new .txt file appears in the folder.

3. Rename this file **SBLConfig.ini**.

**NOTE:** Make sure the file extension is changed to ini, not txt.

4. Double-click this file to open it in Notepad.
  - a. To select a specific language when SMART Board software starts, type the following text:

```
[SBLauncher]
```

```
ShowLanguagePicker=1
```

- b. To select a desktop shortcut when SMART Board software starts, type the following text:

```
[SBLauncher]
```

```
ShowShortcutDialog=1
```

- c. To select both options when SMART Board software starts, type the following text:

```
[SBLauncher]
```

```
ShowLanguagePicker=1
```

```
ShowShortcutDialog=1
```

5. Save the file and close Notepad.

When you start SMART Board software, the messages you added appear.

**First Published:** November 2, 2006

**Last Updated:** November 23, 2007

**SMART Technologies**  
1207 – 11 Avenue SW, Suite 300  
Calgary, AB T3C 0M5  
CANADA



[www.smarttech.com/support](http://www.smarttech.com/support) [www.smarttech.com/contactsupport](http://www.smarttech.com/contactsupport)  
Support +1.403.228.5940 or Toll Free 1.866.518.6791 (Canada/U.S.)

© 2006–2007 SMART Technologies ULC. All rights reserved. SMART Board, smarttech and the SMART logo are trademarks or registered trademarks of SMART Technologies ULC in the U.S. and/or other countries. All other third-party product and company names may be trademarks of their respective owners. Patent No. US5448263; US6141000; US6326954; US6337681; US6741267; US6747636; US7151533; and CA2058219. Other patents pending. Contents are subject to change without notice. 11/2007.